

## LFC316X Cooker Hood



### Stylish, effective cooking

Our cooker hood mounts right into the wall to give you more space while matching your existing decor. Plus its powerful performance handles cooking odours and removes them without a fuss. Enjoy simpler mealtimes in an odour-free kitchen.

### Hood settings, made simple

Your cooker hood functions can be easily reached with our mechanical controls. Adjust the light settings or the fan speed for fast, flexible cooking.

### Clean filter, clean air.

This filter provides continually effective protection for your kitchen. And, because it's fully washable, it works to provide cleaner air in your kitchen for even longer.

### More Benefits :

- A reliable way to reduce cooking smells for cleaner air in kitchen

#### Features :

- Push button controls with 3 speeds
- Washable aluminium grease filters
- Recirculation or extraction options
- Noise level: dB(A)
- For wall mounting between furniture or as a stand alone unit

#### Technical Specs :

- Installation : Chimney
- Size : 60
- Dimensions, HxWxD : 690-940x598x450
- Minimum distance from cooking top : 50
- Minimum distance from cooking top : 65
- Cord Length : 1.4
- Voltage : 220-240
- Required Fuse : No
- Frequency : 50
- Colour : Stainless steel
- Charcoal filter type : ECFB02
- Other comments technical specifications : max height is for exhausting mode. For recirculatory mode: max 990
- Superperforming charcoal filter compatible : NO, NO
- Energy class : D
- Fluid dynamic efficiency class : E
- Lighting efficiency class : E
- Grease filter efficiency class : D
- Capacity minimum, m3/h : 235
- Capacity, Max m³/h : 420
- Sound power min speed, dB(A) : 53
- Sound power max speed, dB(A) : 66
- No. of speed settings : 3
- Lamp type : LED bulb
- No. of lamps : 2
- Grease filters : 2
- Recirc sound power min, dB(A) : 60
- Recirc sound power max, dB(A) : 73
- Recirculation min, m3/h : 175
- Recirculation max, m3/h : 245
- ProdPartCode : B - Open All

#### Product Description :

## LFC316X Cooker Hood

PSGBCH180DE0000W

